



ARGOPLUS-1500-L10POD-DALI

CLEVERTRONICS Argonaut Plus 1500mm Weatherproof Emergency Batten, L10 with POD, Switchable Colour, DALI Emergency



PRODUCT INFORMATION	
Product Code	ARGOPLUS-1500-L10POD-DALI
MIC	UKB01220160002
Description	Argonaut Plus 1500mm Weatherproof Emergency Batten, L10 with POD, Switchable Colour, DALI Emergency
Colour CCT	Switchable 3000K / 4000K (Default) / 5700K
Output Configuration	Fixed Single Output
Battery Configuration	Batteries contained within thermally isolated POD for optimum battery life
Construction	Polycarbonate Base and Diffuser w/Stainless Steel Clips (SS304)
Diffuser	Polycarbonate
Mounting	Surface Mount
Operating Mode	SUSTAINED
Testing System	DALI Registered
Battery	Lithium Nanophosphate, 3.3V 5000mAh
Charging Method	Intelligent current limited constant voltage
Sensor Capability	n/a
Dimensions LxWxH (mm)	1630x160x105
Weight (kg)	3.9
Driver / Ballast	LED Driver - LC 57w 800-1050mA, flexC Ip
Lamp(s)*	LED strip module, 3000K / 5700K, Ra>80 L70/B50 Ta 40°C; LM80 Report >60,000hr, Projected 157,000hr L80/B20 Ta 40°C; LM80 Report >60,000hr, Projected 95,000hr L90/B10 Ta 40°C; LM80 Report 43,000hr, Projected 43,000hr
Supply Voltage	220-240V~ 50Hz
Power Factor	0.93 @ default
Supply Current	239mA +/-20mA
Inrush Current (Max)	52.0A<250µs
Earth Leakage	0.513mA
Total lumen output	6337 lm (132 lm/W) @ default (refer to next page for details)
Power Consumption	47.8W @ default (refer to next page for details)
Operating Temperature	0°C to 40°C
IP Rating	IP65
Impact Rating	IK08
LED MacAdam Step (SDCM)	4
Rated Emergency Duration	180 minutes
Emergency Lumens	333
Compliance Marking	UK CA CE



ARGOPLUS-1500-L10POD-DALI

CLEVERTRONICS Argonaut Plus 1500mm Weatherproof Emergency Batten, L10 with POD, Switchable Colour, DALI Emergency



PRODUCT INFORMATION

Protection	<ul style="list-style-type: none"> • Battery overvoltage & overcurrent protection • Battery deep discharge protection • Supply voltage polarity reversal protection • Battery short-circuit protection (charging will resume upon removal of fault) • Kit box (enclosure) of lamp controlgear provides protection against accidental contacts with live parts 			
Luminaire Classification	X	2	ADF	180
Conformity	BS IEC 60598-2-22, BS 5266, BS EN IEC 55015, BS EN 61547, BS EN IEC 61000-3-2			

REPLACEMENT PARTS

COMPONENT	PART NUMBER & DESCRIPTION
240V Driver	1330057 - LED Driver - LC 57w 800-1050mA, flexC Ip
240V LED Strip	8002753 - PCA:LED Strip ARGOPPLUS-1500,10P16S,3000K/5700K
Emergency Driver	UKM01270060002 - Lifelight Pro, Control Only, Dali Reg, L10, 415mA
Emergency LED Strip	8050205 - HWSUB: CT10570-A4 - 2 LED WHITE
Battery	1530050 - BATTERY:L10 3.3V 2.5AH 70mm lead, no Brkt
Sensor	n/a

Power Consumption & Lumen Output	Output (950mA)				Lumen Output
	Max Charge, Lamp On	Standby Charge, Lamp On	Standby Charge, Lamp Min. 10% (sensor version only)	Standby Charge, Lamp Off	
3000K	51.9W	49.6W	n/a	0.7W	5877 lm
4000K (DEFAULT)	50.1W	47.8W	n/a	0.7W	6337 lm
5700K	51.8W	49.5W	n/a	0.7W	6185 lm

*The projected value has been calculated by extrapolation of the LM80 data using the Energy Star Calculator

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order